



Model: YO919 Version: 2.8 Date: 16/01/2017

What's in the box

- Yoswit Smart Bulb Converter (YO919) x 1
- E14 Bulb Cap x 1
- B22 Bulb Cap x 1
- E27 Bulb Cap x 1
- User Menu x 1
- Warranty Card x 1



If any of the above items is missing, please contact your reseller.

Preface

Lincogn reserves the right to revise this publication and to make changes in the content hereof without obligation to notify any person or organization of such revisions or changes.

Caution

Please read all of the safety and operating instructions before using your device:

1. Do not use lamps operate at 85°C or above.
2. Beware of the hot product surface while it is operating.
3. Do not open the device or attempt to repair or service it.
4. Use the device in a dry location, and avoid placing it in a humid environment.
5. Do not submerge the device in liquid or attempt to clean it with liquids or solvents. To clean the device, disconnect from the power outlet and use a dry towel.
6. This device should only be used indoors.

Working with Smart Devices

This product can work alone without relying on routers and phones. However, in using a smart phone with our app installed, it allows you to switch your appliances on or off in an instant remotely, and change your power schedules on-the-go, ensuring that you don't have to worry about leaving something on while you're away. For detailed app functions, as this improves from time to time, please refer to the user guide inside the app.

Download the App

1. Download our app from the **a. AppStore** (iPhone, iPad, or iPod touch); **b. Google Play** (Android) or **c. download the app in - apk.yoswit.com**
2. Once the app is installed, launch the app and follow the on-screen instructions.



Introduction

The Yoswit Smart Bulb Converter is a compact, and easy-to-use device that allows you to control your lighting through your smart devices without any installation of extra smart switches or devices.



1.	Bulb Holder	Connect your bulbs (holder type is E27).
2.	Power Button / Reset Button	- Short press the button to turn the connected device on or off. - Long press the button for 5s to reset the password - Long press the button for 20s to reset the device to factory default setup
3.	Bulb Cap	Connect the bulb holder into a lamp holder. There are 3 different bulb caps of your choice.
4.	Cap Lock	Press the button to release the safety lock when replacing the bulb cap.

Installation

1. Make sure the power is turned off.
2. Verify that your bulb are electrically rated to operate with the requirement as stated in the specification.
3. Remove your original light bulb.
4. Insert the Bulb Cap into the lamp holder.
5. Connect the bulb to the Bulb Holder.
6. Switch on the power of your lamp.



Change of Bulb Cap

1. Make sure the product is not connected to power.
2. Use one hand to press the Cap Lock button.
3. Use another hand to hold the cap and turn it anti-clockwise.
4. Open the cap.
5. Proper align the appropriate cap to the bottom of the bulb holder.
6. Hold the cap and turn it to clockwise until the lock is fastened.



Technical Specifications



General

Product Name	Yoswit Smart Bulb Converter
Model	YO919
Compliance	CE, FCC, RoHS
Manufacturer	Designed by Yoswit in Hong Kong. Assembled in China

Electrical

Input Voltage	AC100-240V
Ambient Temperature	-10°C to 50°C
Maximum Load Power	60 watt
Standby Power	<0.1 watt

Mechanical

Cap Type	E14, B22, E27
Holder Type	E27
Surface Materials	V0 flame-resistant PBT + fiberglass
Operating Environment	Indoors (IP 20)
Operating Temperature Range	-10°C to 80°C
Operating Humidity Range	0-90% relative humidity, non-condensing

Bluetooth

Product Compatibility	Bluetooth Smart Ready products
Frequency	2.4GHz
Radio Transmission Power	0~5 dBm
Bluetooth Range	Open area: >50m; indoor: 10-20m
Bluetooth Version	Bluetooth 4.0
Radio Transmission Power	0~5 dBm