

Yoswit Smart Plug (YO602uk)

- User Manual



Model: YO602uk Version: 2.8

Date: 16/01/2017

What's in the Box



Yoswit Smart Plug (YO602uk) x 1



User Manual x 1



Warranty Card x 1



If any of the above items is missing, please contact your reseller

Preface

Lincogn reserves the right to revise this publication and to make changes in the content hereof without obligation to notify any person or organization of such revisions or changes.

Caution

Please read all of the safety and operating instructions before using your device:

- Plug your smart plug directly into your wall outlet. Do not plug the device into an extension cord or other power extender.
- 2. Confirm that your smart plug is plugged properly and fully into your wall outlet.
- $3. \ \ Ensure there is at least 5 cm of distance when you are placing furniture in front of Yoswit smart plug.$
- 4. Do not open the device or attempt to repair or service it.
- 5. Use the device in a dry location, and avoid placing it in a humid environment.
- 6. Do not submerge the device in liquid or attempt to clean it with liquids or solvents. To clean the device, disconnect from the power outlet and use a dry towel.
- 7. This device should only be used indoors.

Working with Smart Devices

This product can work alone without relying on routers and phones. In using a smartphone with our app installed, you can control devices in an instant remotely. It also changes your power schedules, ensuring that you can have a complete control of devices with smart automation wherever you are. For detailed and updated app functions, please refer to the user guide in the app.

Download the App

- Download our app from the a. App Store (iPhone, iPad, or iPod touch); b. Google Play (Android) or c. download the app in apk.yoswit.com
- 2. Once the app is installed, launch the app and follow the on-screen instructions.





Introduction

The Yoswit Smart Plug is a compact, and easy-to-use device that allows you to control your electronic devices through your smart devices without any installation of extra smart switches or devices.



| 1. | Power Button/ Reset Button | - Press the button to turn the connected device on or off - Press and hold the button for 5s to reset the password - Press and hold the button for 20s to reset the device to factory default setup | |
|----|-------------------------------|---|--|
| 2. | LED Indicator | LED indicator lights up if the device is on. | |
| 3. | Plug Connector | Insert the plug of electric devices here to connect the smart plug. | |
| 4. | Plug Pin | Insert the plug pin to the in-wall outlet hole. | |
| 5. | Earth Pin | Component to prevent electrical shocks in case of short circuit. | |

Installation

1. Plug the smart plug into a wall A/C outlet.



2. Insert the plug of electric devices to the plug hole of the smart plug.



3. Turn on the power supply of the electric devices. Press the power button by tapping 2 to 3 times. Your devices will turn on/off.



Technical Specifications



| General | | | | |
|--------------|--|--|--|--|
| Product Name | Yoswit Smart Plug | | | |
| Model | YO602uk | | | |
| Plug Type | UK | | | |
| Version | V1 | | | |
| EAN / UPC | EAN: 0712155479906; UPC: 712155479906 | | | |
| Compliance | CE, FCC, RoHS | | | |
| Manufacturer | Designed by Yoswit in Hong Kong. Assembled in China. | | | |

| Electrical | | | | |
|------------------------|-----------------------------------|--|--|--|
| Input Voltage | AC100-240V | | | |
| Frequency | 50/60Hz Auto Detected at Power-Up | | | |
| Standby Power | <0.1 watt | | | |
| Operating Temperature | -10°C to 40°C | | | |
| Resistive Load Current | 10A | | | |
| Inductive Load Current | 5A | | | |

| Mechanical | | | | |
|--------------------------------|---|--|--|--|
| Surface Materials | V0 flame-resistant PC | | | |
| Operating Environment | Indoors | | | |
| Ingress Protection (IP) | 20 | | | |
| Operating Temperature Range | 10°C to 40°C | | | |
| Operating Humidity Range | 0-90% relative humidity, non-condensing | | | |

| Bluetooth | | |
|--------------------------|------------------------------------|--|
| Product Compatibility | Bluetooth Smart Ready products | |
| Frequency | 2.4GHz | |
| Radio Transmission Power | 0~4 dBm | |
| Bluetooth Range | Open area: >50m; indoor: 10-20m | |
| Bluetooth Version | Bluetooth 4.0 | |