



Model: YO101i Version: 1.0

Date: 12/01/2017

What's in the box

- Yoswit Bluetooth Portable IR Hub (YO101i) x 1
- USB Cable x 1
- User Menu x 1
- Warranty Card x 1



If any of the above items is missing, please contact your reseller.

Preface

Lincogn reserves the right to revise this publication and to make changes in the content hereof without obligation to notify any person or organization of such revisions or changes.

Caution
Please read all of the safety and operating instructions before using your device:

1. Use the device in a dry location, and avoid placing it in a humid environment.
2. Yoswit Bluetooth Portable IR Hub is not for children under 12.
3. Do not submerge the device in liquid or attempt to clean it with liquids or solvents. To clean the device, remove the batteries and use a dry towel.
4. Please install the batteries according to the Installation part and follow the battery manufacturer's safety and usage instructions.
5. Please keep the batteries away from children and pets.
6. Dispose or recycle spent/discharged batteries and damaged/worn Yoswit Bluetooth Portable IR Hub in compliance with all applicable laws.

Working with Smart Devices

This product can work alone without relying on routers and wiring. In using a smart phone with our app installed, it allows you to switch your appliances on or off in an instant remotely, and change your power schedules on-the-go, ensuring that you do not have to worry about leaving something on while you are away. For detailed app functions, as this improves from time to time, please refer to the user guide inside the app.

Download the App

1. Download our app from the a. AppStore (iPhone, iPad, or iPod touch); b. Google Play (Android) or c. download the app in - apk.yoswit.com
2. Once the app is installed, launch the app and follow the on-screen instructions.


Introduction

The Yoswit Bluetooth Portable IR Hub is a portable smart universal remote that allows you to control your Infrared (IR) devices through your smart devices via Bluetooth anywhere.



1.	Power Button	Push the button to left side to turn the device on, and push the button to right side to turn the device off.
2.	Micro USB Port	Insert USB Cable here to connect the Yoswit Bluetooth Portable IR Hub to your power source for charging and constant power supply.
3.	Shortcut keys	Customizable shortcut keys that can be set as phone finder alarm, IR commander, Yoswit Bluetooth products controller, etc. with the assistance of Yoswit's app.
4.	Strap Hole	The hole for you to put on straps or champs to the Yoswit Bluetooth Portable IR Hub.
5.	Hanging Hole	Two hanging hole for mounting the Yoswit Bluetooth Portable IR Hub on the wall.
6.	Battery Compartment	Place two "AAA" size batteries (not included) in the Battery Compartment in order to supply power to the Yoswit Bluetooth Portable IR Hub.

Installation
Warning


1. To prevent any personal injury and/or property damage, do not mix a used battery with a new battery, or mix different chemistries or sizes of batteries.
2. The polarity of batteries should be placed properly.
3. Do not connect the Yoswit Bluetooth Portable IR Hub to your power supply with USB Cable and install batteries to the device at the same time.


Install with batteries

1. Remove the Battery Compartment Cover in the back of Yoswit Bluetooth Portable IR Hub. 
2. Place two "AAA" size batteries into the Battery Compartment, correctly observe the polarity indications (+/-) inside the Compartment. 
3. Replace the Battery Compartment Cover. 
4. Push the button to left side to turn the device on. 

5. Further set up the device with the App.


Install with power supply

1. Insert USB Cable into Micro USB Port to connect the Yoswit Bluetooth Portable IR Hub to your power supply. 
2. Push the button to left side to turn the device on. 
3. Further set up the device with the App. 

Technical Specifications

General

Product Name	Yoswit Bluetooth Portable IR Hub
Model	YO101i
Compliance	CE, FCC, RoHS
Manufacturer	Designed by Yoswit in Hong Kong. Assembled in China.

Electrical

Power Supply Methods	The power supply for Yoswit Bluetooth Portable IR Hub can be 1) two installed "AAA" size batteries (not included); 2) any power supply units connected by Micro USB Cable.
Input Voltage	3V
Standby Time	1 year (using two "AAA" size batteries with 2000 mA)

Mechanical Properties

Plastic	V0 Flame-Resistant PC +ABS
Operating Environment	Indoors (IP 20)
Operating Temperature Range	-10°C to 40°C
Operating Humidity Range	0-90% relative humidity, non-condensing
Storage Conditions	-20°C to 60°C

Bluetooth

Product Compatibility	Bluetooth Smart Ready Products
Frequency	2.4GHz
Radio Transmission Power	0~5 dBm
Bluetooth Range	>50m, open area
Bluetooth Version	Bluetooth 4.2